

FG-1625R/1625RT GLASSBREAK DETECTOR



The new FG-1625R Glassbreak Detector uses the latest technology to provide faster response and increased false alarm immunity. The FG-1625R is specifically designed to allow fast,

easy installation, while the adjustable sensitivity settings can compensate for the acoustics of any room. Optimum operation can be quickly verified using the FG-701 Glassbreak Simulator.

FEATURES

• **FlexCore™ Signal Processor**

The FlexCore Signal Processor is an Application Specific Integrated Circuit (ASIC), which processes sound data in parallel rather than sequentially for faster, more accurate detection decisions.

The combination of proven FlexGuard® performance with the speed of FlexCore processing provides unmatched false alarm immunity without compromising detection.

• **Easy Installation and Setup**

Honeywell's patented technology allows remote activation of Test Mode (with simulator). The FG-1625R has a centered wire entry hole, 45° terminal blocks and EOL terminals. A hand-clap feature verifies the detector is functioning.

• **Selectable Sensitivity**

Two dip switches on the FG-1625R make it easy to set the sensitivity to match the acoustics of room. Four different sensitivity levels are available, ranging from very low to high. The range can then be verified remotely with the FlexGuard FG-701 Glassbreak Simulator.

• **Mount the Detector Anywhere**

Mounts on any wall, in the window frame, or on the ceiling, with no minimum range and a maximum range of 25' (7.6m) to the glass.

• **Covers All Glass Types**

The FG-1625R works on all glass types, including plate, tempered, laminated, wired, film-coated, sealed insulating glass.

• **Multiple Domain Signal Analysis**

The FG-1625R performs Multiple Domain Signal Analysis in which time, frequency and amplitude characteristics are evaluated for signal qualification. This enables the detector to accurately discriminate false alarms from true glassbreak events.

• **Enclosed PC Board**

The PCB is protected from potential damage during installation.

• **Patented Remote Test Mode**

The Patented Remote Test Mode can enable or disable the indicator LEDs remotely using the FG-701 Glassbreak Simulator. The detector automatically resets from Test Mode in five minutes.

• **Mounting Locations**

The FG-1625R can be mounted on the ceiling, opposite wall, adjoining wall, or the same wall as the glass.

FG-1625R/1625RT

GLASSBREAK DETECTOR

SPECIFICATIONS

• Physical Dimensions

White high impact ABS plastic housing
4 1/4" D x 7/8" (11mm x 2.2cm)

• Weight

Product Only: 4.5 oz (128 g)
Pkgd Product: 7.5 oz (215 g)

• Range

25' (7.6m) maximum, omni-directional
Range is adjustable; no minimum range

• Alarm Relay

FG-1625R: Form A, 125 mA max,
25 VDC max
FG-1625RT: Form C, 125 mA max,
25 VDC max

• Tamper Switch (FG-1625RT only)

Combination cover/wall tamper
25mA max, 24VDC max

• Alarm Duration

Five seconds (unaffected by
alarm LED latching)

• ESD Immunity

10kV discharges of either polarity
to exposed surfaces

• Power Requirements

6 - 18VDC, 12 mA typical at 12VDC;
22mA max (Latched LED)
AC ripple: 4V peak-to-peak at
nominal 12VDC

• RFI Immunity

30V/m, 10 MHz - 1000 MHz

• Operating Temperature

14° to 122° F (-10° to 50° C)

• Storage

-4° to 122° F (-20° to 50° C)

• Approvals and Listings

- FCC and IC verified
- CE
- C-Tick
- UL Listed
- ULC Listed

• Glass Type/Thickness

Type*	Minimum	Maximum
Plate 3a	2.4mm (3/32")	10mm (3/8")
Tempered	3mm (1/8")	10mm (3/8")
Laminated 1	3mm (1/8")	14mm (9/16")
Wired	6mm (1/4")	6mm (1/4")
Coated 2, 3b	3mm (1/8")	6.4mm (1/4")
Sealed	3mm (1/8")	6mm (1/4")
Insulating 1,3b	Maximum overall 7/16"	

* Minimum size for all types is 28cm
(11") square; glass must be framed
in the wall or mounted in a barrier at
least 0.9m (36") wide.

1. Protected only if both plates of the
unit are broken.

2. Coated glass with security films,
including films for solar protection,
up to 12 mil. thick may be used. Film
Technologies International, Inc.'s
GLASS-GARD® GGLL 1200 has
been evaluated with this product by
Underwriters Laboratories, Inc.

3. In compliance with Underwriters
Laboratories of Canada's Standard
for Intrusion Detection Units
(CAN/ULC-S306-M89):
 - a. Plate glass 3mm to 10mm can
be used.
 - b. ULC recognizes a maximum range
for protecting sealed insulated
glass and coated glass of
12.5 ft. (3.8m).

Note: The FG-1625R/1625RT detects shattering
of framed glass by direct impact. It may not
consistently detect breakage by blows that only
crack the glass, by high velocity projectiles such
as bullets or glass broken without an impact.

• FlexGuard®

Glassbreak Simulator/Tester

The sound of breaking glass is digitally
simulated by the FG-701. The FG-701
is compatible for testing all Honeywell
glassbreak detectors. Honeywell highly
recommends testing glassbreak
detectors before final installation.

ACCESSORIES

FG-701 P/N 0-000-701-0

Glassbreak Simulator

ORDERING

FG-1625R/1625RT

Glassbreak Detector Round Case (FG1625RT with Tamper)

Automation and Control Solutions

Honeywell Security & Communications
2 Corporate Center Dr. Suite 100
P.O. Box 9040
Melville, NY 11747
www.honeywell.com

L/FG1625R/D
September 2008
© 2008 Honeywell International Inc.

Honeywell