


# 4208SN

## V-PLEX® SERIALIZED EIGHT ZONE REMOTE POINT MODULE



The 4208SN Remote Point Module (RPM) is an eight-zone expander that allows the use of available expansion zones on Honeywell VISTA controls that support V-Plex polling loop devices.

### FEATURES

- Can be used on controls that support up to 250 zones
- Can be optionally powered from an external DC power supply to reduce the amount of current draw from the polling loop
- Uniquely identified eight EOLR supervised zones (all zones use 10K resistors, supplied)
- Each zone is identified by a unique serial number, which is assigned via on-board DIP switches
- Detects faults on all zones within 400ms of occurrence
- Loops A & B can be programmed for fast (10ms) response
- Provides cover tamper protection, which may be enabled or disabled via on board DIP switches

### SPECIFICATIONS

#### Physical

- 6-7/16" W x 4-1/4" H x 1-1/4" D (163mm x 108mm x 32mm)

#### Electrical

##### Polling Loop Voltage

- 11V nominal; 8.7 - 14VDC range

##### Current

- 33.6mA when polling loop provides power to module, 0.6mA when 12VDC input provides power to module. See chart below.

##### 12VDC Input Voltage

- 12V nominal; 9.4 - 14VDC range

#### Expander Sensor Loop Response

- Slow: 400msec (all loops)
- Fast: 10msec (option for loops A and B)

#### Expander Sensor Loop Current

- 0.52mA (normal)
- 1.3mA (shorted)

**NOTE:** These currents apply when polling loop input = 11VDC and 10VDC input is not connected to external supply

#### Sensor Loop Max. Resistance

- Up to 300 ohms of wire resistance + 10K EOLR

#### Agency Listings

- UL985 Household Fire
- UL1023 Household Burglary
- UL609 Commercial Burglary
- UL864 Commercial Fire
- CSFM
- FM (Pending)
- CUL
- CE (requires #N6361)

#### For UL Listed Commercial Fire Usage:

Use N.O. contacts. Style B supervise these loops using Model #EOL 100 fire listed 10K EOLRs (purchased separately).

#### For UL Listed Commercial Burglary Usage:

Use N.O. or N.C. contacts. Supervise using EOLRs supplied.

Power Input Source	Current Draw (all zones shorted)	
	From Polling Loop	From External Power
Polling Loop Only	33.6m	N/A
Polling Loop and External Power Input	0.6mA	33mA

### ORDERING

4208SN

Eight Zone Expander

For more information: [www.honeywell.com/security/hsc](http://www.honeywell.com/security/hsc)

#### Automation and Control Solutions

Honeywell Security & Communications  
2 Corporate Center Dr. Suite 100  
Melville, NY 11747  
1.800.467.5875  
[www.honeywell.com](http://www.honeywell.com)

L/4208SND/D  
May 2009  
© 2009 Honeywell International Inc.

# Honeywell