



This programmable, handheld remote can directly communicate via IR for device control, RF for device control via MRF base stations and Wi-Fi for voice integration via Amazon Alexa and Comcast Xfinity. The brilliant 2.4" color LCD screen features Free Format customization allowing graphic placement anywhere on the screen. When used with a compatible Complete Control base station, like the MRF-350 and MRF-260, the MX-1400 controls integrated A/V components through walls and cabinet doors, or even from outside. There is no need to point the remote control at the components or even be in the same room.

SPECIFICATIONS

SKU	MX-1400, MX-1400i
UPC	656787-705180 (MX-1400), 656787-705197 (MX-1400i)
Memory	Flash Memory 512Mb
Wi-Fi	Quick Connect 2.4 GHz [For Voice Control]
LCD	2.4" Capacitive Touch Display
IR Range (Line of Sight via Infrared)	30 to 50 feet, depending on the environment
RF Range (Radio Frequency)	50 to 100 feet, depending on the environment
RF Frequency	418 MHz (MX-1400), 433 MHz (MX-1400i)
Microphone	2 CH MIC
Speaker	Mono 1.5W x 1
Battery	Lithium Polymer, 3.7V, 1700mAh
Battery Charging Time	2.5 Hours
Power	5.0V 2.0A
Operating Temp	32 - 104 F / 0~40 °C
Dimensions	W: 1.96" / 50mm H: 7.87" / 220mm D: 0.94" / 23.8mm
Weight	Remote: 6.23oz / 176.7g (with battery loaded) Cradle: 4.93oz / 139.8g
System	Complete Control® Professional programming required
In The Box	MX-1400 Remote Control, Charging Dock, USB Type-C Cable, Power Adapter, Li-ion Rechargeable Battery
Warranty	Please visit www.urb-automation.com/warranty