

Trove2PH2 (Enclosure & Backplane) / TCV2 (Backplane)

Access and Power Integration Solutions



Altronix Trove™ enclosures and backplanes let you easily integrate Altronix power with Openpath access controllers. Trove simplifies board layout and wire management, reduces installation time and labor costs.



Trove2PH2

* Boards not included



Trove2PH2 (Trove2 Enclosure + TCV2 Backplane) Features

- Accommodates the following Openpath controllers with or without Altronix power/accessories:
 - Openpath one (1) OP-ACC, OP16EM, and one (1) OP-EX-4E or OP-X-8E
 - Altronix Power Supply
 - Altronix Sub-Assemblies
- Includes Altronix Trove2 Enclosure and one (1) removable TCV2 backplane

Agency Listings

UL:

UL294 - Access Control System.

cUL:

CAN/ULC - s319-05 - Electronic Access Control Systems.

CE

European Conformity.

Features

- Simplifies board layout and wire management
- Convenient knockout configuration:
 - One (1) single knockout 2.415" (2" Conduit).

Features (cont'd)

- Sixteen (16) double knockouts
1.362" (1" Conduit) / 1.115" (3/4" Conduit).
- Accommodates up to four (4) 12VDC/7AH batteries
- 16 AWG powder coated steel
- Includes cam lock, tamper switch and mounting hardware

Trove2PH2 - Dimensions (H x W x D):

27.25" x 21.5" x 6.5" (692.15mm x 546.1mm x 165.1mm)

Trove2PH2 - Weights:

Product - 37.1 lb. (16.83 kg)
Shipping - 40.85 lb. (18.53 kg)

TCV2 - Dimensions (H x W x D):

25.375"H x 19.375"W x 0.3125"D
(644.5mm x 492.1mm x 8mm)

TCV2 - Weights:

Product - 8.0 lb. (3.63 kg)
Shipping - 10.0 lb. (4.53 kg)

Access Controller Position Chart for the Following Models:

| Altronix / Openpath | Pem Mounting |
|---|--------------|
| AL400ULXB2, AL400ULXB2V, AL600ULXB, AL600XB220, AL1012ULXB, AL1012XB220, AL1024ULXB2, AL1024XB2V, eFlow4NB, eFlow4NBV, eFlow6NB, eFlow6NBV, eFlow102NB, eFlow102NBV, eFlow104NB, eFlow104NBV, Tango1B | (A) |
| ACM8, ACM8CB, ACMS8, ACMS8CB, LINQ8ACM, LINQ8ACMCB | (B) |
| ACM4, ACM4CB, LINQ8PD, LINQ8PDCB, MOM5, PD4UL, PD4ULCB, PD8UL, PD8ULCB, PDS8, PDS8CB, VR6 | (C) |
| OP-ACC | (D) |
| OP-EX-4E | (E) |
| OP-EX-8E | (F) |
| OP-16EM | (G) |



