



FVT-2001 Version: 1

RJ45 to SC Fast Ethernet Media Converter, Multi-Mode Fiber, 2km

The FVT-2001 MMF SC media converter is able to convert network signals between copper and fiber-optic based networks. The converter provides a 10/100Base-TX RJ-45 port, supports full duplex and half duplex switch connectivity and 10Base-T and 100Base-TX auto-sensing. Used in multi-mode with fibre-optic cabling, this can extend a network range up to 2km.

The device features built-in Dip switches for easy converter configuration, which function on the Smart LFP (Link Fault Pass-through), allowing the converter to monitor both the fiber and copper ports for signal loss, as well as converter transmission method, auto-negotiation mode for adjusting copper speed and full & half duplex mode.

The FVT-2001 is able to operate in temperatures from -10° up to 55° Celsius. The converter can be used as a standalone unit or as a slide-in module to the CHV-2000 19" Converter Chassis, which can accommodate up to 14 units for use in a central wiring closet.



1. 10/100Mbps Fiber Port
2. LED Indicators
3. 10/100Mbps RJ-45 Port



4. DC Power Jack
5. Dip Switch

Key Features

- Transfers data from 10/100Base-TX copper to fiber interfaces
- Multi-mode fiber with SC connector for transmission of up to 2km
- Built-in LFP (Link Fault Pass-through) (LLCF/LLR) Technology
- IEEE 802.3x Flow Control protects against lost packets for reliable data transmission
- Dip switches for customized configuration
- Supports low-time lag transmission
- Supports the transmission of extra-long packets up to 1.6KB



- -10°C to 55°C operating temperature range

Works With



CVH-2000

14-Slot Media Converter Chassis



FVT-2002

RJ45 to ST Fast Ethernet Media Converter, Multi-Mode Fiber, 2km

Specifications

System Specifications

Standards & Protocols:

IEEE 802.3 10-BASE-T, Ethernet

IEEE 802.3u 100-BASE-TX, Fast Ethernet

IEEE 802.3x Flow Control (full-duplex flow control)

Port:

1 x 100Base-FX Multi-mode duplex SC

Fiber cable: 50/125um, 62.5/125um

1 x 10/100Base-TX RJ-45 Port, auto MDI/MDI-X and Auto-Negotiation

Indicator:

PWR, TX (FDX, 100, Link/Act), FX (100, Link/Act)

Wavelength (nm):

1310nm

Transmission Method:

Store and forward (Default)

Power Input:

DC 5V/1A

Operating Temperature (°C):

Storage: -40 ~75 °C

Operating: -10 ~ 55 °C

Operating Humidity (Non-condensing):

5 ~ 90 %

Mount:

Desk, chassis mounted

Features

General:

DIP Switch 1: LFP function

DIP Switch 2: Transmission Mode

DIP Switch 3: Auto/Force the UTP port work mode

DIP Switch 4: 10/100M for UTP port

DIP Switch 5: Full/Half Duplex mode for UTP port

DIP Switch 6: Normally close



Order Information

FVT-2001

Package Contents

FVT-2001

Power Adapter

Quick Installation Guide

Optional Accessory



CVH-2000

14-Slot Media Converter Chassis

No liability or responsibility for any errors or omissions in the content.
Specifications are subject to change without notice.
All mentioned brand names are registered trademarks and property of their owners.
Copyright © Digital Data Communications GmbH, Germany. All Rights Reserved.