

IX Series Video Door Streaming

The IX Series video door station can be streamed to a VMS or NVR using the ONVIF Profile S or RTSP connection methods. The IX video door station is treated like any other IP camera and will require a license on the VMS or NVR. By default, IX Series video door stations have the second video stream turned on and set to stream using the H.264 protocol. When configuring, verify door station settings.

ONVIF Profile S

The IX Series video door station supports ONVIF Profile S. The stream is on by default and the username and password for the video stream is:

Username: aiphone

Password: aiphone

RTSP

RTSP Stream URL

rtsp://[ip address]/udp/unicast/aiphone_H264

rtsp://[ip address]/udp/unicast/aiphone_JPEG

Username: aiphone

Password: aiphone

or

rtsp://aiphone:aihone@[ip address]/udp/unicast/aiphone_H264

rtsp://aiphone:aihone@[ip address]/udp/unicast/aiphone_JPEG

Note:



When using the default H.264 protocol, enter the address ending in H264.

For MJPEG, use IX Support Tool to change the streaming method of the video door station and enter the address ending in JPEG.

Tested VMS/NVR

Manufacturer	Product	Method	Type
Aimetis	Aimetis Symphony	RTSP	VMS
Avigilon	ACC5, ACC6, ACC7	RTSP or ONVIF (ACC7)	VMS
Dahua	DH-NVR-4216-8P	ONVIF	VMS
Digifort	Digifort	ONVIF	VMS
Exacq	ExacqVision	RTSP	VMS
FLIR (formerly DVTEL)	Latitude 7.0	RTSP	VMS
Genetec	Security Center	ONVIF	VMS
HikVision	DS-7608NI-E2/8P	ONVIF	NVR
IPConfigure	Enterprise Surveillance Manager	RTSP	VMS
Lenel	OnGuard	RTSP	VMS
Messo	NVR203-004	RTSP	VMS
Milestone	Xprotect	ONVIF	VMS
Onssi	Ocularis	ONVIF	VMS
Pelco	DS ControlPoint	ONVIF	VMS
S2 Security	S2 NetVR	RTSP	VMS
Sony	NSR500	ONVIF	NVR
Video Insight	VI Monitor	ONVIF	VMS

For more details about the features and information above, please contact Technical Support.

Aiphone Corporation | www.aiphone.com | tech@aiphone.com | (800) 692-0200