

Trove1SA1

Access and Power Integration Solution for Salto



Altronix Trove1SA1 consists of a high-capacity enclosure with removable backplane. This unit easily combines Altronix power/accessories with various combinations of Salto CU42E0 controllers in a streamlined package. Trove simplifies board layout and wire management, reducing installation time and labor costs.



Trove1SA1

* Boards not included



Trove1 Enclosure + TSA1 Backplane Features

- Accommodates Salto boards with or without Altronix power supplies/sub-assemblies.
 - Salto: CU42E0, CU4EB8, CU4200
 - Altronix power supplies/sub-assemblies
- Includes Altronix Trove1 Enclosure and one (1) removable TSA1 backplane.

Agency Listings

UL:

UL294 - Access Control System.

cUL:

CAN/ULC - s319-05 - Electronic Access Control Systems.

CE

European Conformity

Features

- Simplifies board layout and wire management.
- Convenient knockout configuration:
 - One (1) double knockout 1.948" (1-1/2" Conduit) / 1.701" (1-1/4" Conduit).
 - Nine (9) double knockouts 1.362" (1" Conduit) / 1.115" (3/4" Conduit).
- Accommodates up to two (2) 12VDC/7AH batteries.
- 16 AWG powder coated steel.
- Includes cam lock, tamper switch and mounting hardware.

Dimensions (H x W x D):

18.0" x 14.5" x 4.625" (457.2mm x 368.3mm x 117.5mm)

Weights:

Product - 15.15 lb. (6.87 kg)
Shipping - 19.05 lb. (8.64 kg)

TSA1 Backplane Features

- Accommodates Salto CU42E0 boards with or without Altronix power supplies/sub-assemblies.
- Backplane features:
 - Simplifies board layout and wire management.
 - 16 AWG galvanized steel.

Dimensions (H x W x D):

16.625" x 12.5" x 0.3125" (422.3mm x 317.5mm x 8mm)

Weights:

Product - 3.35 lb. (1.52 kg)
Shipping - 4.0 lb. (1.81 kg)


Trove1SA1

Access and Power Integration Solution for Salto



Access Controller Position Chart for the Following Models:

Altronix / Salto	Pem Mounting
AL400ULXB2, AL400ULXB2V, AL600ULXB, AL600XB220, AL1012ULXB, AL1012XB220, AL1024ULXB2, AL1024XB2V, eFlow4NB, eFlow4NBV, eFlow6NB, eFlow6NBV, eFlow102NB, eFlow102NBV, eFlow104NB, eFlow104NBV, Tango1B	(A)
ACM4, ACM4CB, LINQ8PD, LINQ8PDCB, MOM5, PD4UL, PD4ULCB, PD8UL, PD8ULCB, PDS8, PDS8CB, VR6	(B)
CU42E0, CU4EB8, CU4200	(C)



Trove1SA1

Access and Power Integration Solution for Salto

