

#### Description

Altronix T1MK14SD kit consists of Trove1 enclosure and TM1 Altronix & Mercury backplane with 12VDC or 24VDC (factory set at 24VDC) @ 4A power supply/charger, 12VDC voltage regulator, eight (8) PTC protected output dual voltage power distribution module and four (4) PTC protected output access control module. This kit also accommodates various combinations of Mercury\* boards for up to four (4) doors in a single enclosure. Trove simplifies board layout and wire management, reduces installation time and labor costs.

\*Also compatible with these authentic Mercury partners:

AccessNsite, Avigilon, BadgePass, BluBox, Feenics, Genetec, Identocard, IMRON, Johnson Controls, Kastle, Keri Systems, Lenel/S2, LockState, Maxxess, Midpoint Security, NLSS, Open Options, Panasonic Video Insight, Quintron, RS2, Schneider Electric, Vanderbilt



T1MK14SD

#### Key Features

- Accommodates the following Mercury controllers:  
Mercury: LP1501, LP1502, LP2500, LP4502, MR16IN, MR16OUT, MR50, MR52, MR62e, MUX8
- Convenient knockout configuration:
  - One (1) double knockout  
1.948" (1-1/2" Conduit) / 1.701" (1-1/4" Conduit)
  - Nine (9) double knockouts  
1.362" (1" Conduit) / 1.115" (3/4" Conduit)
- 16 AWG galvanized steel backplane simplifies board layout and wire management
- Supervision
  - AC Fail
  - Supervision (*cont'd*)
    - Battery Fail and Battery Presence
- Agency Listings:
  - All Altronix components of this Trove kit are UL Listed sub-assemblies. Please refer to the Sub-Assembly Installation Guides for further information
    - UL: UL294 - Access Control System
    - cUL: CAN/ULC - s319-05 - Electronic Access Control Systems
    - CE European Conformity
- Enclosure accommodates up to two (2) 12VDC/7AH batteries
- Lifetime Warranty\*

\*Altronix Power Supply/Chargers and Sub-Assemblies only

#### Accessories (order separately)



WM5

#### WM5, WM25, WM100 - Magnetic Cable Tie Mounts

Altronix WM5, WM25, and WM100 are packs of 5, 25 or 100 magnetic cable tie mounts respectively. They accommodate standard zip ties or velcro straps. These are ideal for wire management in our Trove series.



Mounting Magnet

#### MM4, MM8, MM12, MM24 - Magnetic Mounting Solution

Altronix mounting magnets accommodate screws and nylon standoffs to allow for mounting various boards/ accessories in any metal enclosure or backplane.

# T1MK14SD

## Access & Power Integration Solution

### Specifications

#### Power Supply (AL400ULXB2):

##### Input

Voltage	115VAC, 60Hz, 3.5A max
Fusing	5A / 250V

##### Output

Voltage	12VDC or 24VDC selectable
Current	4A @ 12VDC or 3A @ 24VDC continuous max
Other	Oversvoltage protection. Filtered and regulated

#### Battery Backup

Capacity	7AH / 12VDC (Up to 2 within enclosure) 40 AH / 65 AH (requires separate enclosure)
Type	Sealed lead acid or gel type
Fuse Rating	15A/32V
Failover	Upon AC loss, instantaneous

#### Supervision

AC Failure	Form "C" contacts
Battery	Form "C" contacts

#### Indicators (LED)

Input	115VAC is present
DC Output	Powered
Battery	Discharged or not connected

#### Dual Input Power Distribution Module (PDS8CB)

##### Input

Voltage	12VDC from VR6 and 24VDC from AL400ULXB2
Input PTC	9A

##### Outputs

Voltage	12VDC and/or 24VDC
Any of the eight (8) power outputs are selectable to follow power Input 1 or Input 2	
Individual outputs may be set to OFF position for servicing	

##### Outputs Ratings

PTCs	2.5A
------	------

#### Indicators (LED)

DC Output	Eight (8) individual output LEDs
Green:	12VDC
Red:	24VDC

#### Voltage Regulator (VR6):

##### Input

Voltage	24VDC from AL400ULXB2
---------	-----------------------

#### Voltage Regulator (VR6) (cont'd):

##### Output

Voltage	12VDC
Current	6A continuous
Other	Surge suppression

#### Indicators (LED)

Input	24VDC is present
Output	Powered

#### Access Power Controller (ACM4CB):

##### Input

Voltage	24VDC from AL400ULXB2
Input Fuse	10A/32V

##### Outputs

Voltage	24VDC
Four (4) independently controlled 2.5A outputs:	
a) Four (4) Fail-Safe and/or Fail-Secure power outputs	
b) Any combination of the above	
Four (4) auxiliary power outputs (unswitched)	

##### Outputs Ratings

PTCs	2.5A
------	------

#### Indicators (LED)

Red LEDs	Outputs are triggered (relays energized)
Green LED	FACP disconnect is triggered

#### T1MK14SD Kit:

##### Agency Listings

All components of this Trove kit are UL Listed sub-assemblies. Please refer to the corresponding Sub-Assembly Installation Guides for further information.

CE	European Conformity.
----	----------------------

#### Physical and Environmental:

##### Dimensions (H x W x D)

18" x 14.5" x 4.62" (457.2mm x 368.3mm x 118.0mm).

##### Weight (approx.)

Product	16.23 lbs. (7.36 kg)
Shipping	20.23 lbs. (9.07 kg)

##### Temperature

Operating	0°C to 49°C (32°F to 120°F).
Storage	-20°C to 70°C (-4°F to 158°F).

Relative Humidity 85% +/-5%

BTU/Hr. (approx.): 90 BTU/Hr

**Access Controller Position Chart for the Following Models:**

Mercury	Pem Mounting
LP2500, MUX8	(A)
LP1502, LP4502, MR52, MR16IN, MR16OUT	(B)
LP1501, MR62e	(C)
MR50	(D)



