



### E-114-3 Emergency Pull Cord Stations



#### ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

The Emergency Pull station(s) shall be Alpha Communications® / Cornell E-114-3, or approved equal with latching pull cord operated switch, mounted on a durable Stainless Steel faceplate marked "EMERGENCY" and "PULL FOR HELP", permanently silk-screened onto the faceplate.

Unit shall mount on single-gang electric "gem" box or plaster ring. Unit shall feature a 'Latching' Normally-Open switch that activates when the six (6) foot nylon cord is pulled. Unit shall have pigtail wire connectors.

A built-in RED 'Call-Placed' lamp shall light when the pull cord station is activated.

The Emergency Call switch may be used with many 'stand-alone' emergency systems.

Contractor shall observe all local and national electrical and building codes.

#### E-114-3 EMERGENCY PULL CORD STATIONS

The Alpha Communications® / Cornell E-114-3 Emergency Pull station is used to initiate a system 'Emergency' signal. It may be used independently or connected with other call stations and/or intercom stations. The E-114-3 has a DPST Normally-Open switch that activates in a 'Latching' fashion, when the pull cord is pulled. In addition, a built-in RED 'Call-Placed' lamp will light when the pull cord station is activated.

Placing a call is accomplished by pulling on the pull cord. This type of 'Latching' pull cord station is typically canceled by sliding the switch back to the up (OFF) position. The E-114-3 station features a rugged stainless steel faceplate, with the word 'EMERGENCY' and "PULL FOR HELP" permanently silk-screened onto the faceplate.

#### FEATURES

- Simple, reliable operation
- Call cancel only at point of origin
- Red 'Call-Placed' Lamp
- Call registers at Master Station and on (optional) Dome Lamp
- Mounted on stainless steel faceplate permanently stamped with the word 'EMERGENCY' and 'PULL FOR HELP'

#### SPECIFICATIONS

<b>Dimensions:</b>	Height: 4.50" (114mm) Width: 2.75" (69mm) Depth: 1.50" (38mm) Projects: 0.50" (13mm) from mounting surface
<b>Mounting:</b>	Steel City #52171 box with Steel City #52C14 plaster ring, or Alpha Communications® Model #IH358 box with IH357 ring, or EXACT EQUAL. Vertical mount
<b>Construction:</b>	Reliable Components mounted to a Stainless Steel faceplate
<b>Connection:</b>	Plug-in Connectors

#### Alpha Communications

42 Central Drive • Farmingdale • NY • 11735-1202 • Phone: (631) 777-5500 • Fax: (631) 777-5599  
TOLL-FREE: (800) 666-4800 • Web: [www.alphacommunications.com](http://www.alphacommunications.com) • Email: [info@alphacommunications.com](mailto:info@alphacommunications.com)