

VISTA-50P/50PUL

SPECIFICATIONS:

APPLICATION OPTIONS

- Wireless remote control – single button system operation:
 - 5804 – a four button programmable wireless key
 - 5804BD – a bi-directional button programmable wireless key with system status feedback
- Single or dual button wireless personal panic:
 - 5802MN – 5802MN2
- Home control features that activate lights, appliances, garage doors, and numerous other devices
- Vista Interactive Phone Module (VIP) that gives the end user control of their system from any touchtone phone. The 4285 VIP responds in English, with a vocabulary of over 100 words
- Full English display keypads for clear understanding of system status and zone locations
- Time event applications:
 - Opens garage doors and turns on lights
 - Provides “lived in look” while away from home
 - Can limit access to parts of the home at certain times

TECHNICAL SPECIFICATIONS

Electrical:

- Aux power 12 VDC, 750mA max
- 16.5 VAC/40 VA transformer
- Alarm output 12 VDC, 2.8 Amps max
- For UL installations, combined Aux and alarm output cannot exceed 750mA

Output Control:

- Supports up to four relay boards and 16 outputs (part no. 4204)
- Optional X-10 transformer/interface (part no. 4300) maybe used to control X-10 receiving devices
- Each X-10 receiver address counts as one relay when computing total relays
- Real time clock can be used for relay/ X-10 control

Zones:

- Eight hardwired zones
 - Selectable response: 10msec, 350msec, 750msec
 - Assignable to any partition
 - 16 zone types to choose from
 - Programmable swinger suppression

SUPPORTED DEVICES

Hardwired Expansion Devices:

- 4208U eight zone expansion module
- Powerline support – 4300 transformer/interface
- Keypads
 - 6139 custom English (required for programming) – 100mA
 - 6128 fixed English LCD – 85mA/40mA
- Voice module 4286 VIP – 160mA
- Two-wire smoke detectors
- Duct detectors
- Polling loop devices
- Keyswitch devices

WIRELESS RECEIVER SYSTEMS

- 5800 Series
 - 5881L up to 8 zones – 50mA
 - 5881M up to 16 zones – 50mA
 - 5881H up to 86 zones – 50mA
- All receivers support:
 - Diversity reception with two antennas
 - Remote mounting for best location
 - Use of second receiver for maximum coverage or tough installations
 - Unique supervision and low battery indications by point

TRANSMITTERS

- 5800 Series
 - Three volt Duracell lithium batteries
 - One mile range
 - Tamper standard

AGENCY LISTINGS

- UL Residential Fire and Burglary and CFM
- UL Commercial Burglary when using the VISTA-50PUL

COMMUNICATIONS

- Touchtone or pulse
- Formats supported: ADEMCO Contact ID®, ADEMCO 4 + 2 Express, ADEMCO Low Speed
- 3+1, 4+1 and 4+2 reporting
- Reporting capabilities: split, dual, split/dual
- Low battery reports 11.2–11.6 VDC
- Expanded reporting
- Up to four digit PABX code supported
- True dial tone detection
- Double pole line seizure
- AC loss and restoral reporting supported

Control
Panel

ORDERING:

Part No.	Description
VISTA-50P	Control Panel
VISTA-50PUL	Control Panel UL Commercial