

909022008 – DIN rail power supply with 12/24V battery charger @ 99W

Battery charger leads are supplied as standard to easily connect a battery back-up capability.



The features for the PAC 7A switchable power supply are:

- High Quality power supply that can switch between 12V and 24V DC outputs
- The PSUs come in a DIN rail mountable form.

For battery back-up the following batteries are needed in addition:

- One 7Ah 12V DC battery is required for a 12V DC PSU
- Two × 7Ah 12V DC batteries connected in series are needed for a 24V DC PSU

Part Number(s)	909022008 – DIN rail power supply with 12/24V battery charger
Power input(s)	100-230V AC
Power output(s)	13.8V @ 7 Amp / 27.6V @ 3.5 Amp
Frequency (power)	50/60Hz
Dimensions	90 (w) × 176 (h) × 45 (d) mm / 3.54 (w) × 6.93 (h) × 1.77 (d) in.
Weight	0.616 kg / 1.358 lb
Operating Temperature	-20°C to +50°C / -4°F to 122°F
Warranty	5 years against electronic failure
Standards Compliance	UKCA, CE, UL, FCC, IC, RoHS & WEEE compliant