

## Substituting the WMT1A Line Matching Transformer for the TL600 Plug-In Transformer for use with BPA and HTA Series Power Amplifiers



### Instructions:

1. Confirm that the WMT1A jumper is installed for LINE input as shown in **Figure 1**.
2. At the RCA inputs of either the BPA or HTA amplifiers, connect the WMT1A RCA plug to either of the HI-Z RCA inputs. The low-impedance screw terminal inputs on the rear of these amplifiers will not be used for this application.
3. Turn the amplifier input level control fully CCW, or off.
4. Connect your signal source cable to the outer two balanced 600-ohm input screw terminals on the WMT1A, with ground being the center terminal, if used (**Figure 2**).
5. With the signal source live, adjust the input level of the amplifier as needed.

