
Appendix F: Wiring Diagrams

HS2016, HS2032, HS2064, HS2128 UL/ULC Wiring Diagram

HS2016/2032/2064/2128 UL/ULC Wiring Diagram



ULC NOTES

smoke detector is required.

Model: HS2128 FCC Reg. No. F53AL01BPHS2128 REN = 0.1B Plug Type: RJ-31X MADE IN CANADA

- For ULC Listed Fire Monitoring Installations & module requirements, please refer to the ULC Installation Information Sheet, part #29002157.
- Use a CSA/cUL transformer, hardwired
- This device complies with Parts 15 and 68 of the FCC rules. Operation is subject to the following 2 conditions: [1] this device may not cause harmful interference and [2] this device must accept any interference received, including interference that may cause undesired operation. All tamper circuits may be connected to the same
 - · Use ULC-LA for AC Power indication.

(a) The delay (power-up) time marked on the installation wiring diagram of the smoke detector or on the installed smoke detector(s) is to be used.

Control panel is suitable for the following UL installations: (1) Grade AA Central Station and Grade AA Police Connect with high line security (using T-LINK to communicate to the Sur-Gard MLR-IP Receiver). (2) Household Fire and Grade A Household Burglay and Home Health Care Signaling Equipment (3) Grade A Local Grade B Central Station and Police Connect with basic line security (4) Grade C Central Station. Refer to Installation Manual