

DRA-12/24 Remote indicator plate, 12/24V

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Easy wiring to D7050-B6
- ▶ Attractive faceplate
- ▶ Highly-visible alarm LED

The DRA-12/24 Remote indicator plate (12/24V) provides remote annunciation of alarms when connected to the D7050-B6 MUX base, 2-wire. It flush-mounts or surface-mounts on a single-gang box and has an alarm LED.

Certifications and approvals

Region	Regulatory compliance/quality marks	
USA	UL	ANSI/UL 268, Smoke Detectors for Fire Alarm Systems
	CSFM	see www.boschsecurity.com (the Bosch website)
Canada	ULC	CAN/ULC-S527, Control Units for Fire Alarm Systems

Installation/configuration notes

Compatible Products

The DRA-12/24 Remote Annunciator is compatible with the D7050-B6 MUX base, 2-wire

Wiring Considerations

When using 18 AWG (ISO 0.75 mm²) wire, mount the DRA-12/24 ≤ 500 ft. (152 m) from the receiver. When using 22 AWG (ISO 0.34 mm²), mount the DRA-12/24 ≤ 200 ft. (61 m) from the receiver.

Parts included

Quantity	Component
1	DRA-12/24 Remote indicator plate, 12/24V
1	Literature - Installation manual

Technical specifications

Mechanical

Dimensions (H x W x D)	4.85 in. x 3.1 in. x 0.25 in. (12.3 cm x 7.9 cm x 0.6 cm)
------------------------	--

Electrical

Current	5 mA
12 VDC	10 mA
24 VDC	
Voltage	12 VDC or 24 VDC nominal

Ordering information

DRA-12/24 Remote indicator plate, 12/24V

Provides remote annunciation of alarms when connected to the D7050-B6 MUX base, 2-wire
Order number **DRA-12/24**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia