

# Securitron® XMS Exit Motion Sensor

*Versatile motion detection  
for hands-free exit request*



The XMS passive infrared (PIR) motion sensor request to exit (REX) device reliably detects motion near a door and releases its lock.

Versatile mounting options and an easily adjustable infrared beam pattern provide optimal coverage of the egress area for smooth, hands-free lock release and exit.

*Safety Note: ASSA ABLOY Electronic Security Hardware recommends that an emergency exit button, such as the EEB, be used in conjunction with the XMS to meet applicable building codes and specific life safety issues.*

## How to Order

Model Series

**XMS**

**XMS** Exit Motion Sensor



MagnaCare  
Warranty



Dual Voltage  
12/24

## Features

### Standard Features

- Passive infrared (PIR) request to exit (REX) device
- Automatically and reliably cuts power to the lock with no human intervention
- REX output
- Easily adjustable beam pattern
- Adjustable time relock
- MagnaCare® lifetime replacement, no fault, no questions asked warranty

## Specifications

### Certifications

- ANSI/UL 294 Listed

### Dimensions

- 7" L x 1-7/8" W x 1-3/4" H
- Indoor use only

### Electrical

- 20 mA-50 mA (depending on switching status) at 12 or 24 VDC

### Shipping Weight

- 0.5 lbs [0.23kg]

