

60 Watt P.A. Amplifier with AM/FM Tuner & MP3 Ready CD Player

P60FACD 60W P.A. amplifier

Features

- 4 zoned 70 or 25V speaker outputs
- AM/FM Tuner with 8-function CD player
- Telephone paging input and Music-on-hold output
- Individual volume control for each Mic input
- Front bass and treble controls
- Mic1 selectable priority paging
- UL & CSA listed
- 5 year warranty



rear of unit

Specifications

RMS Output Power.....	60W
Max. Output Power.....	90W
AC Power Consumption ...	170W
Power Supply	AC 115V, 50Hz/60Hz
Zones.....	4
Speaker Outputs.....	4/8/16 Ohms (non-zoned), 70/25V (zoned)
Other Outputs	Aux (RCA)
Inputs.....	1 x AM Antenna (Press terminal), 1 x FM Antenna (BNC), 1 x Aux (Stereo RCA), 4 x Mic (XLR), 1 x TEL (terminal)
Frequency Response	60Hz ~ 15kHz (±3dB)
Tone Control	Bass ± 10dB, Treble ± 10dB
THD	Less than 1% @ 1kHz
Signal/Noise Ratio	70dB
Controls	Volume for each Mic, Master Volume, Vox Volume, MoH Volume, Vox Selector, Tone, Source Selector, Zone Selector, Tuner and CD
Telephone	TEL in and MoH Out
Indicators	Tuner, CD, power, power level
Dimensions.....	16.9" (W) x 3.5" (H) x 11.6" (D)
Weight	21.4 lbs.
Listings	UL, cUL, CSA, CE, FCC

Rack mounting kit available: **PBMRK2**