

Programmable IR/RF Remote Control with 2.4" LCD



OVERVIEW

Versatile programmable handheld remote provides single-room IR control – TV, A/V components, cable and satellite boxes. It is ideal for home theater installations and A/V control in kitchens and bedrooms. When used with a compatible Complete Control base station, it controls A/V components through walls and cabinet doors, even from outside – no need to point the remote or be in the same room.

- Handheld remote with brilliant 2.4" color LCD – displays up to eight buttons per screen
- Ergonomic design with backlit hard button keypad and on-board speaker
- Delivers single-room, one-way control of IR devices
- Controls A/V through walls and cabinet doors, or from outside
- Lithium-ion rechargeable battery with tabletop charging cradle
- MX-990i features 433 MHz frequency for international and highly-populated markets

HIGHLIGHTS

- Custom Interface** Custom user interface with font library allows dealer to create custom icons, layouts, themes, backgrounds and sounds
- Pickup Sensor** Wakes up when lifted, preserves battery charge
- Timers** Event and Sleep Timers for automated event scheduling
- IR** Range 30-50 feet, frequency 15 kHz to 455 kHz
- RF** Range 50-100 feet, frequency 418 MHz (MX-990), 433 MHz (MX-990i)
- Ports** Micro USB port for dealer programming
- Conditional Logic** Features conditional logic for advanced programming
- File Import** Enables dealer to import existing MX-980/MX-980i program files

SPECIFICATIONS

SKU	MX-990, UPC 656787-399907 / MX-990i, UPC 656787-388857
System	Complete Control™ - Professional programming required
In the Box	Handheld remote, rechargeable battery, charging cradle, AC adaptor, USB cable, room labels
Dimensions	2.32" W x 8.98" H x .87" D
Weight	6.21 oz. with battery
Warranty	1 year limited USA warranty



914.705.4148



completecontrol@universalremote.com



UniversalRemote.com

