



**Product Overview:**

Designed to adapt our LA-326 Rack Mount Kit to accept antenna mounting, the LA-125 includes a 90-degree helical antenna and can be used to build your own antenna for specific application and installation needs. Compatible with our LT-800 transmitter and LR-100 receiver, the antenna provides excellent coverage for small and medium venue.

**Highlights:**

- Converts the LA-326 rack mount kit to allow a 90-degree antenna to be mounted
- Includes our 90-degree helical antenna
- Allows you to build a custom antenna for your specific application
- Provides a transmission range of up to 122 m (400 ft.)

**Includes:**

- One (1) LA-125 90° Helical Antenna (72MHz)
- One (1) 18 in. BNC to BNC Cable
- One (1) BNC feed-through Connector
- One (1) Manual

Product Specification: Antenna Kit for Rack Mount (72 MHz)	
<b>Interconnections</b>	
Connector/s	BNC
<b>RF</b>	
Frequency Range	72.0250 - 75.9500 MHz
Number of Channels	57 (17 wide, 40 narrow)
Typical Range	Range up to 122 m / 400 ft.
<b>Physical</b>	
Length	8.75 in. (22.22 cm)
Color	Dark Grey
Shipping Weight	1 lb. (0.5 kg)
Diameter	0.44 in. (1.10 cm)
Cable Length	18 in. (46 cm)
Weight	4.2 oz. (119 g)