



CL01

Professional
PTZ Camera Controller

Take Control of Your Video

Take control of your productions like a pro with this robust and intuitive solution to manage your video capture and broadcast needs. Compatible with all AVer Auto Tracking and PTZ cameras and a variety of other brands. With a simple configuration to manage up to 7 cameras, the CL01 provides the power of a mini studio on your desk.



Pan/Tilt/Zoom
Speed Control



Operate 255
PTZ Cameras



3 Infinite
Rotation Knobs



Multiple Control
Interfaces



VISCA Pelco-D/P
Pelco-P
Protocols



1-Year Warranty

An All-in-One Controller to Meet Your Unique Production Needs



Higher Education



Enterprises



House of Worship



Government Agencies

Product Specifications

I/O Interface	Communication	RS-485, RS-422, RS-232, IP, Micro USB for firmware upgrades
	Baud Rate	2400, 4800, 9600, 19200, 38400 bps
User Interface	Display	OLED display screen
	Rotation Button	3
	Camera Shortcut Channel	7
	Joystick	1
	Keyboard	Backlit Keys
Camera Control	IP Address	Default: 192.168.1.162 / 163 / 164 / 165 / 166 / 167 / 168 (from Cam 1 to Cam 7)
	UDP Port	52381
	Cam ID	1 to 7 and more (255* max.)
	Control Protocol	VISCA, SONY VISCA , Pelco-D/P, UDP, IP (VISCA over IP)
System	Operating Temperature	0°C ~ 40°C (32°F ~ 104°F)
	Dimensions	173 mm (W) x 99 mm (H) x 350 mm (D)
	Gross Weight	2.5 kg
	Power Source	DC 12V/2A, AC 100~240V
	Power Consumption	24 W
	Application	Indoor
	Package Content	User manual / 4-pin RS485 terminal / power adapter
	Part Number	PTCAMCTRL

* After setting up the multi-channel function, select the camera and then press CAM 7 to start controlling it.
Specifications may vary depending on location and are subject to change without notice.

Hardware Specifications



AVer Information Inc. Americas
668 Mission Court, Fremont, CA 94539
Toll free 1.877.528.7824 T 408.263.3828 F 408.263.8132

©2021 AVer Information Inc. All rights reserved.
All brands and logos are trademarks of their respective companies. Specifications subject to change without notice

pro.averusa.com