



Product Overview:

Designed to mount to the rear BNC antenna connector, the LA-123 antenna offers an outstanding coverage range up to 600 ft (182.88 m). The 90-degree antenna is compatible with the 72 MHz versions of our LT-800 transmitter, LR-100 receiver/amplifier, and the LR-600 receiver/speaker. The LA-123 is also included with the LA-125, allowing the antenna to be placed in front of the equipment rack for specific application and installation needs.

Highlights:

- Outstanding coverage up to 122 m (400 ft.)
- Mounts with a BNC connector
- Compatible with 72 MHz equipment including our LT-800 transmitter and LR-100 receiver

Includes:

One (1) LA-123 90° Helical Antenna (72MHz)

Product Specification: 90 Degree Helical Antenna (72 MHz)	
Interconnections	
Connector/s	BNC
RF	
Frequency Range	72.0250 - 75.9750 MHz
Number of Channels	57 (17 wide, 40 narrow)
Typical Range	Range up to 122 m / 400 ft.
Physical	
Length	21.0 cm (8.25 in.)
Color	Dark Grey
Shipping Weight	0.5 kg (1 lb.)
Diameter	1.10 cm (0.44 in.)
Weight	45 g (1.60 oz.)