



# SuperSpeed+ USB-C 3.1 to HDMI Converter

C Male to HDMI Female, Black

Part No.: 151788

Easily connect a USB type-C source with a HDMI display.

The Manhattan USB 3.1 to HDMI Converter establishes a fast, simple and convenient link between newer USB type-C equipped media sources (computers, tablets, etc.) and existing HDMI displays (monitors, projectors, etc.). The Manhattan USB 3.1 to HDMI Converter is easy and quick to install--no complicated configuration or setup required. Its all-in-one design achieves a compact, integrated solution that eliminates unnecessary cables, tangles and clutter to keep installations and work spaces neat and orderly. Extend the service life of your equipment, and fully realize the investment and value of your HDMI displays, projectors and peripherals with Manhattan USB 3.1 to HDMI converters.

#### Features:

- Converts USB video and audio to a HDMI signal
- Enjoy Ultra high-definition (UHD) images on a HDMI monitor, projector or other display device
- Supports video resolutions up to 3840x2160p@30Hz, 4K, Full UHD
- Compliant with DisplayPort 1.2 Alternate Mode (DP Altmode)
- Plug and Play; requires no external power supply
- Compatible with all USB type-C supported desktops, notebooks and tablets including Apple MacBook, Chromebook Pixel and more
- Fully shielded to reduce EMI and other interference sources
- Molded PVC boot and strain relief
- Lifetime Warranty

## **Specifications:**

Standards and Certifications

- USB 3.1
- HDMI
- HDCP 1.4
- CE
- FCC



## manhattan-products.com

- RoHS2
- WEEE

#### Connections

- USB type-C, 24-pin, male
- HDMI, 19-pin, female
- Shielded

#### Video Resolutions

• 640 x 480, 800 x 600, 1024 x 768, 1920 x 1200, 3840 x 2160p@30Hz, 4K

## Physical

- 32-AWG cable gauge
- · Mylar and aluminum shielding
- Thermal plastic casing
- Length: 8 cm (3 in.)
- Weight: 31 g (1.1 oz.)
- Shielded
- Housing: ABS plastic

## **Operating Environment**

- Operation Temperature: 32 ~ 122°F (0 ~ 50°C)
- Storage Temperature: -4 ~ 185°F (-40 ~ 85°C)
- Humidity (noncondensing): 0 ~ 96%

### System Requirements

Windows XP/Vista/7/8.1/10 or Linux or Mac 9.x/10.x or above

### **Package Contents**

• SuperSpeed+ USB 3.1 to HDMI Converter







## manhattan-products.com





