



The Inovonics EN1235D double-button belt clip pendant features a rugged, double-button design to help prevent false alarms.

### Product Features

Double-button design helps prevent false alarms
Can be worn on the belt clip or mounted for fixed position signaling
LED flashes with all transmissions, ensuring operation at a glance
Belt clip included

### Product Specifications

Dimensions:	3.0" x 1.6" x 0.72" (7.6 cm x 4 cm x 1.8 cm)
Weight:	2 oz (57 g)
Typical battery life:	3 to 5 years
Internal battery type:	Panasonic CR2
Accessories:	ACC605-BK10 pendant black belt clip, ten pack
Operating environment:	
Temperature:	32°F to 140°F (0°C to 60°C)
Humidity:	Up to 90% (non-condensing)
Market:	North America, Australia, New Zealand
EchoStream® frequency:	902-928 MHz, frequency hopping spread spectrum
Check-in time frequency:	3 minutes
Regulatory compliance:	FCC, RoHS

## Reference Materials (available at [www.inovonics.com](http://www.inovonics.com))

---

[EN1233S/D and EN1235S/D EchoStream Pendant Transmitter Installation Instructions](#)

---

[EchoStream Developer Guide](#)

---

[EchoStream One-Way Security Developer Guide](#)

---

[Inovonics Product Catalog: North America](#)

---

- The range and performance of any wireless product depends on the structure and environment in which it operates.
- Continual enhancements to our products may cause specifications to change without notice.
- Patents: 7,154,866; 7,554,932; 7,746,804; others pending.
- Inovonics supports recycling and reuse whenever possible. Please recycle these parts using a certified electronics recycler.

## Technical documents

---

For technical documents visit us at <http://www.inovonics.com/support/tech-documents/> or use the QR code below.

