

Magnetic Lock

Comparison Chart



	320S	600S	600L	600LB	600D	600DLB	600WP
Holding Force	300 lbs	600 lbs	600 lbs	600 lbs	600 lbs per magnet	600 lbs per magnet	600 lbs
Electrical							
12 VDC Current Draw	250 mA	505 mA	505 mA	505 mA	505 mA, per magnet	505 mA, per magnet	505 mA
24 VDC Current Draw	130 mA	260 mA	260 mA	260 mA	260 mA, per magnet	260 mA, per magnet	260 mA
Field Selectable 12 or 24 VDC ♦	●	●	●	●	●	●	●
♦ Refer to catalog for additional information regarding electrical consumption.							
Specification							
UL 10C Listed		●	●	●	●	●	
UL 294 Listed		●	●	●	●	●	
CAN4-S104 / CAN-ULC-S533 Listed		●	●	●	●	●	
ULC-S527 Listed		●	●	●	●	●	
UL 864 Listed		●	●	●			
Features							
Bond Sensor				●		●	
Door Status Signal				●		●	
Status LED			●	●		●	
Door Application							
Glass Door w/ Aluminum Frame (Light Security)	●	●	●	●	●	●	●
Wood Door (Light Security)	●	●	●	●	●	●	●
Wood Door (High Security)							
Metal Door (Light Security)	●	●	●	●	●	●	●
Metal Door (High Security)							
Herculite Door (w/out Top or Bottom Rail*)		●	●	●	●	●	
Herculite Door (w/Top or Bottom Rail*)		●	●	●	●	●	
Cabinets	●						●

● = Preferred application
 * With correct mounting accessories

Magnetic Lock

Comparison Chart *cont.*



	1200S	1200L	1200LB	1200D	1200WP
Holding Force	1200 lbs	1200 lbs	1200 lbs	1200 lbs per magnet	1200 lbs
Electrical					
12 VDC Current Draw	505 mA	505 mA	505 mA	505 mA, per magnet	505 mA
24 VDC Current Draw	260 mA	260 mA	260 mA	260 mA, per magnet	260 mA
Field Selectable 12 or 24 VDC ♦	●	●	●	●	
♦ Refer to catalog for additional information regarding electrical consumption.					
Specification					
UL 10C Listed	●	●	●	●	
UL 294 Listed	●	●	●	●	
CAN4-S104 / CAN-ULC-S533 Listed	●	●	●	●	
ULC-S527 Listed	●	●	●	●	
UL 864 Listed	●	●	●	●	
Features					
Bond Sensor			●	●	
Door Status Signal			●	●	
Status LED		●	●	●	
Door Application					
Glass Door (w/ Aluminum Frame)					
Wood Door (Light Security)					
Wood Door (High Security)	●	●	●	●	●
Metal Door (Light Security)					
Metal Door (High Security)	●	●	●	●	●
Herculite Door (w/out Top or Bottom Rail*)	●	●	●	●	
Herculite Door (w/Top or Bottom Rail*)	●	●	●	●	
Cabinets					

● = Preferred application
 * With correct mounting accessories