

## C2G USB 1.1 Over Cat5 Superbooster<sup>TM</sup> Extender Wall Plate Kit Part No. CG-29342



This plug-and-play device consists of a transmitter unit and a receiver unit incorporated into two, single gang wall plates. The transmitter/receiver pair is connected via standard Cat5, Cat5E, or Cat6 patch cables (not included) allowing for easy in-wall installation. This provides a clean, finished installation that is important for homes, classrooms, offices or any other facility where you don't want unsightly visible cables lying around.

Use pre-terminated network cables or pull unterminated cable and terminate with toolless IDC RJ45 connectors (included). Buspowered, the USB superbooster wall plate requires no external power source. Compliant with USB Specification 1.1.

Transmitter Connectors: One USB Type B Female (Input) and One RJ45 Female (Output)

Receiver Connectors: One RJ45 Female (Input) and One USB Type A Female (Output)

Please Note: The power demands of devices such as external drives and USB hubs may require the use of external power for proper operation.

Note: If the USB signal is being extended to support an interactive whiteboard, then we recommend using our product



## Features & Benefits

Extends a USB 1.1 signal up to 150ft over category cables

Transmitter and receiver are built into wall plates

Patented, Patent No. US 7,741,562

Allows for flexible positioning of USB peripherals

Kit includes both the transmitter and receiver units

## **Specifications**

## General Info

Product Line	C2G	Color	White
UPC Number	757120293422	Country Of Origin	China

Application Sector	Residential, Commercial	Туре	Extender, Wall Plate, Kit
Additional Information			
Prop 65 Warning Required	Yes	Prop 65 Warning Language	Cancer and Reproductive Harm
Technical Information			
Number of Gangs	1	Data Transfer Rate	12 Mbps
Adapter Rear	USB-A Female	Adapter Front	USB-B Female