



# Pure IP™ reader controller accessories

# Overview

Schlage® offers a variety of accessories and replacement parts to ensure your reader controllers are always secure and performing well.

### Reader controller covers

Replacement reader covers can be used to replace faded or cracked covers.

### Advanced security module

Add an additional level of security for exterior doors, the advanced security module kit prevents the lock wires from being in contact with the unsecure side of the door.

### Quick-connect cable

The quick connect cable allows the installer to connect the necessary reader controller wires without the hassle of the reader controller hanging off the other end. Simply connect the wiring harness and plug the reader controller in, it's that easy.

### Magnetic lock kit

This part protects your reader controller from in-rush voltages and is primarily used for magnetic door locks.



Reader covers



**Advanced Security Module** 



**Quick-connect cable** 









Part	Cover	Cover	Cover
Part number	47317541	47317539	47317540
Corresponding controller reader model	RC11	RC15	RCK15
Reader controller type	Mullion	Single gang	Single gang with keypad
Dimensions (HxWxD)	5.91" x 1.72" x 0.81"	5.1" x 3.25" x 0.76"	5.1" x 3.25" x 0.76"
Material	PNT polymer	PNT polymer	PNT polymer

# Color options



(standard)







Part	Quick connect cable/pigtail	Advanced Security Module (ASM)	Magnetic lock kit - In rush suppresso
Part number	47274561 - 10 FT Cable 47274562 - 25 FT Cable	47317537	47317538
Product specifications	<ul> <li>12 pin snap-in MOLEX connector</li> <li>Jacketed cable for protection and improved cable pulls</li> <li>12 conductor cable, 22 AWG wires</li> <li>Cable jacket pre-stripped for connections to the door's components</li> <li>Being detachable simplifies the system's maintenance and troubleshooting</li> </ul>	<ul> <li>Durable plastic enclosure</li> <li>Polycarbonate blend, UV stabilized</li> <li>Potted for greater weather resistance</li> <li>Powered by Schlage reader-controller; no additional power required</li> <li>Rated for 3 amps at 12v DC</li> <li>Proprietary encrypted serial data</li> <li>2 sets of terminal blocks for easy installation</li> <li>Two LED indicators</li> <li>Required for magnetic lock installations powered via PoE</li> <li>Dimensions: 2 3/4" X 1 1/4" X 3/4"</li> </ul>	<ul> <li>Any installation that is using magnetic locks that are equipped with a "quick-release feature" should have this in-rush protection installed</li> <li>Dimensions: 1<sup>1</sup>/<sub>4</sub>" x 1<sup>1</sup>/<sub>4</sub>" x 2 <sup>1</sup>/<sub>4</sub>"</li> </ul>

Allegion, the Allegion logo, Schlage and the Schlage logo are trademarks of Allegion plc, its subsidiaries and/or affiliates in the United States and other countries. All other trademarks are the property of their respective owners.

## **About Allegion**

Allegion (NYSE: ALLE) is a global pioneer in safety and security, with leading brands like CISA®, Interflex®, LCN®, Schlage®, SimonsVoss® and Von Duprin®. Focusing on security around the door and adjacent areas, Allegion produces a range of solutions for homes, businesses, schools and other institutions. Allegion is a \$2 billion company, with products sold in almost 130 countries. For more, visit www.allegion.com.



© 2020 Allegion 013623, Rev. 09/20 www.allegion.com/us

