



Product Overview:

Made for permanent installations, the LA-116 flexible dipole antenna can be mounted on a wall, inside a drop ceiling, or anywhere that requires discreet placement and extended range. Configured for use with our 72 MHz transmitters and receivers, the LA-116 is 203 cm (80 in.) in length and flexible to fit any space or venue where it is needed.

Highlights:

- Flexible for many different applications
- For use with 72 MHz products
- Easy to install
- Transmission range of up to 244 m (800 ft.)

Includes:

One (1) LA-116 Coaxial Dipole Remote Antenna (72 MHz)

Product Specification: Coaxial Dipole Remote Antenna (72 MHz)	
RF	
Frequency Range	72.0250 - 75.9500 MHz
Typical Range	Range up to 244 m / 800 ft.
Physical	
Material	Polyethylene Insulation, PVC Jacket, tinned copper conductor, tinned copper braided shield
Shipping Weight	0.5 kg (1.0 lb)
Diameter	4.88 mm (0.19 in.)
Cable Length	7.62 m (25 ft.)
Cable Type	RG-58 50 Ohm Coaxial
Weight	0.38 kg (13.40 oz.)