

Programmable IR/RF Remote Control with 2.4" LCD



OVERVIEW

Versatile programmable handheld remote provides single-room IR control – TV, A/V components, cable and satellite boxes. It is ideal for home theater installations and A/V control in kitchens and bedrooms. When used with a compatible Complete Control base station, it controls A/V components through walls and cabinet doors, even from outside – no need to point the remote or be in the same room.

- Handheld remote with brilliant 2.4" color LCD displays up to eight buttons per screen
- Ergonomic design with backlit hard button keypad and on-board speaker
- Delivers single-room, one-way control of IR devices
- Controls A/V through walls and cabinet doors, or from outside
- Lithium-ion rechargeable battery with tabletop charging cradle
- MX-990i features 433 MHz frequency for international and highly-populated markets

HIGHLIGHTS

Custom Interface Custom user interface with font library allows dealer to create

custom icons, layouts, themes, backgrounds and sounds

Pickup Sensor Wakes up when lifted, preserves battery charge

Timers Event and Sleep Timers for automated event scheduling

IR Range 30-50 feet, frequency 15 kHz to 455 kHz

RF Range 50-100 feet, frequency 418 MHz (MX-990), 433 MHz (MX-990i)

Ports Micro USB port for dealer programming

Conditional Logic Features conditional logic for advanced programming

File Import Enables dealer to import existing MX-980/MX-980i program files

SPECIFICATIONS

SKU	MX-990, UPC 656787-399907 / MX-990i, UPC 656787-388857
System	Complete Control™ - Professional programming required
In the Box	Handheld remote, rechargeable battery, charging cradle, AC adaptor, USB cable, room labels
Dimensions	2.32" W x 8.98" H x .87" D
Weight	6.21 oz. with battery
Warranty	1 year limited USA warranty







