



AXIS T8341 PIR Motion Sensor

Wireless motion detector

AXIS T8341 PIR Motion Sensor detects motion both day and night, thanks to passive infrared technology. By communicating wirelessly with AXIS M5065 PTZ Network Camera or connected Z-Wave Plus® controllers, the motion sensor can be used in small security solutions with less cabling. The wireless I/O connectivity also enables flexible installation as the sensor can easily be moved and adapted to your needs, even for mounting in corners.

- > Wireless I/O connectivity
- > Z-Wave Plus® compatibility
- > S2 security compliant
- > Battery included





AXIS T8341 PIR Motion Sensor

Supported products	AXIS M5065 PTZ Network Camera Compatible with other Z-Wave Plus® control devices
Network	
Supported protocols	Z-Wave Plus®. For more information on the supported command classes, see the product's User Manual
General	
Casing	Plastic Color: white
Sustainability	PVC free
Power	1 x CR123 3.0 V Lithium battery Battery life: 1 year
Distance	Transmitting range up to 100 meters (328 ft)
Frequency	908.42 MHz (US), 922.5 MHz (JP)
Operating conditions	-10 °C to 40 °C (14 °F to 104 °F)
Storage conditions	-20 °C to 60 °C (-4 °F to 140 °F)
Approvals	EMC FCC Part 15 Subpart B Class B, ICES-003 Class B, VCCI Class B
Dimensions	62 x 42 x 87 mm (2.44 x 1.65 x 3.43 in)
Weight	72 g (0.15 lbs)
Included accessories	Installation guide, mounting kit, 1 x CR123 3.0 V Lithium battery
Warranty	Axis 3-year warranty, see www.axis.com/warranty

Environmental responsibility:

www.axis.com/environmental-responsibility



