Old world craftsmanship. . .tomorrow's technology®

# CAST MR-16 Tree Lights (CCTL1C & CCTL2C) Product Information

# CAST MR-16 Tree Lights in Bronze (CCTL1C) and Oil-Rubbed Brass (CCTL2C)



#### **Dimensions:**

Shroud, base and bracket

(fully extended): 14" long x 2.25" wide.

# **Specifications:**

Lamp: 12v MR-16 (50w max.)

Tree Mount Hardware Kit (CTREEH1) not included.

# **Listing:**

U.L 1838 Listed Low Voltage Luminaire for wet locations

### **Construction:**

Heavy-duty copper shroud; solid bronze (CCTL1C) or oil-rubbed brass (CCTL2C) base, knuckle and bracket; borosilicate convex lens; ceramic socket with solid nickel contacts and stainless steel spring; stainless steel set screws; 35' tin-coated #16-2 No-Ox® marine-grade wire; silicone rubber O-rings.

# **Description:**

CAST rugged MR-16 Tree Lights feature a heavy gauge copper shroud with a solid bronze (CCTL1C) or oil-rubbed brass (CCTL2C) base, knuckle, and mounting canopy.

#### **Features:**

- Heavy-gauge, extra-long, copper shroud with exceptional glare control
- Solid bronze (CCTL1C) or oil-rubbed brass (CCTL2C) knuckle can be adjusted to any angle
- Solid bronze (CCTL1C) or oil-rubbed brass CCTL2C) mounting bracket features quick release for one-handed installation
- Stainless steel mounting hardware sets bracket away from tree to prevent damage from mold and fungus (included - CTREEH1)
- Pre-wired with 35' tin-coated No-Ox® marine grade wire
- High-temp socket with solid nickel contacts
- Includes heat shield to protect socket
- Spider Splice<sup>®</sup> ready

#### **Uses:**

Suitable for mounting in trees or on structures to provide natural downlighting or moonlighting effect.

