




* All images in this datasheet are for illustrative purposes only and may differ from the actual product.



Full HD Standard Signage 32SM5J

LG webOS Standard Signage



webOS Signage
Smart Platform



Built-in Speaker



Support Landscape
/ Portrait Mode



Compatibility with
Promota


32SM5J

Size	32"
Operation Time	24 hrs / 7 days
Brightness	400 nits
Screen Resolution	1,920 x 1,080
LG's Solution Compatibility	Promota App, LG ConnectedCare
Built-in Speakers	10W x 2



HIGH-PERFORMANCE WITH webOS 6.0


The LG webOS smart signage platform has an intuitive user interface and provides system integrators and software developers simple app development tools such as an SDK (Software Development Kit), SCAP (security Content Automation Protocol) and sample applications.



VARIOUS SENSOR CONNECTIVITY

The LG webOS smart signage platform helps provide additional solutions by supporting USB connections with external sensors* such as GPIO, NFC/RFID, temperature, etc.

* External sensors sold separately.



MOBILE & WEB MONITORING


SuperSign Control and Control+ are basic signage control software that can manage up to 100 displays through a single account and server.* Power, volume, and scheduling can be remotely adjusted and firmware updates supported.

* LG SuperSign Control+ is sold separately.



COMPATIBLE WITH AV CONTROL SYSTEM

The SM5J series supports Crestron Connected® for high compatibility with professional AV controls to achieve integration and network-based control, simplifying management of your AV system.



REAL-TIME LG ConnectedCare SERVICE

Maintenance is easy and fast with the optional LG ConnectedCare* service, a cloud service solution provided by LG. It remotely manages the status of your displays across various workplaces for fault diagnosis and remote-control services.

* LG ConnectedCare service sold separately.



LG's SIMPLE ADVERTISEMENT HELPER, PROMOTA

Using LG's Promota* mobile application, you can easily create your own display contents. With Promota, you can add text and images to create an online profile for your business as well as deliver information such as event news, seasonal menus, promotions, and even more to your customers while leveraging easy-to-use templates relevant to your industry.

* Promota can be downloaded from the App Store and Google Play store.



REAL-TIME PROMOTION

With Beacon and Bluetooth® Low Energy (BLE), shop managers can provide coupons and information in real-time.


CONTENT SHARING

Content Mirroring among devices is available on a Wi-Fi network.

WIRELESS ACCESS POINT

The SM5J series operates as a virtual router which can be an wireless access point for mobile devices.

CONNECTIVITY



* Jack Panels may differ from the above image, so please contact LG sales team to verify before ordering.

PANEL	32SM5J	
Screen Size	32"	
Panel Technology	IPS	
Back Light Type	Direct	
Aspect Ratio	16:9	
Native Resolution	1920 x 1080 (FHD)	
Refresh Rate	60 Hz	
Brightness (Typ.)	400 nits	
Contrast Ratio	1100:1	
Viewing Angle(H x V)	178 x 178	
Color Depth	8bit, 16.7 Million colors	
Response Time (G to G)	10 ms	
Surface Treatment (Haze)	1%	
Lifetime (Typ.)	30,000 Hrs	
Operation Hours (Hours/Day)	24/7	
Portrait / Landscape	Yes / Yes	
SOUND	Built-in Speakers 10W x 2	
CONNECTIVITY	HDMI In Yes (x3), HDCP2.2	
	RS232C In 3.5mm stereo jack	
	RJ45 In (LAN) Yes	
	IR In 3.5mm stereo jack	
	USB 2.0 Type A In Yes (x2)	
	Audio Out Yes (Off/Fixed/Variable)	
	RS232C IN Yes	
MECHANICAL	Bezel Color Black	
	Bezel Width 13mm (T/R/L), 18mm (B)	
	Weight 11.9 lbs. / 5.4 kg	
	Weight with Stand 13.7 lbs. / 6.2 kg	
	Shipping Weight 14.8 lbs. / 6.7 kg	
	Dimensions (W x H x D) 28.7 x 16.9 x 2.2 in 729.4 x 428.9 x 55.5 mm	
	Dimensions with Stand (W x H x D) 28.7 x 18.9 x 6.1 in 729.4 x 481 x 154.2 mm	
	Shipping Dimensions (W x H x D) 31.9 x 20.1 x 5.2 in 810 x 510 x 132 mm	
	VESATM Standard Mount Interface 200 x 200	
FEATURES	Internal Memory 8 GB	
	Built-in Wi-Fi Yes	
	Temperature Sensor Yes	
	Auto Brightness sensor Yes	
	Local Key Operation Yes	
	webOS Signage version ver. 6.0	
	Local Contents Scheduling Yes	
	Group Manager Yes	
	USB Plug & Play Yes	
	Fail over Yes	
	Bootimg Logo Image Yes	
FEATURES	32SM5J	
	No Signal Image Yes	
	RS-232C Sync Yes	
	Local Network Sync Yes	
	Screen Share Yes	
	Video Tag Yes (x2)	
	Play via URL Yes	
	Screen Rotation Yes	
	External Input Rotation Yes	
	Gapless Playback Yes	
	Setting Data Cloning Yes	
	SNMP Yes	
	ISM Method Yes	
	Auto Set ID Yes	
	Status Mailing Yes	
	Control Manager Yes	
	Crestron Inside Yes	
	Smart Energy Saving Yes	
	PM mode Yes	
	Wake on LAN Yes	
	Network Ready Yes	
	Beacon Yes	
	HDMI-CEC Yes	
	SI Server Setting Yes	
	webRTC Yes	
	Pro:Idiom Yes	
ENVIRONMENT & POWER	Operation Temperature 32°F to 104°F / 0°C to 40°C	
	Operation Humidity 10 % to 80 %	
	Power Supply 100-240 Vac, 50/60 Hz	
	Power Type Built-In Power	
	Power Consumption (Typ.) 55 W, 187.67 BTU/Hr	
	Power Consumption (Max.) 75 W, 255.91 BTU/Hr	
	"Power Consumption (Smart Energy Saving)" 38.5 W	
	Power Consumption (DPM) 0.5 W	
	Power Consumption (Power off) 0.5 W	
LG SOFTWARE	SuperSign CMS Yes	
	SuperSign Control / Control+ Yes / Yes	
	SuperSign WB Yes	
	SuperSign Media Editor Yes	
	Signage 365 Care Yes	
WARRANTY & OTHER	Warranty 3 Year Limited	
	Regulatory FCC Class "A" / CE	
	Basic Accessories Remote Control (includes 2 batteries), Power Cord, QSG, HDMI Cable, Phone to RS232C Adapter	
	Optional Accessories Stand (ST-322T), Wall Bracket (LSW230B), VESA Adapter (AM-B220S), OPS Kit (KT-OPSF)	