

# Quam QC10P

QC10P is a single-gang, 20W, ten-step, continuous rotary, audio level attenuator with a 24VDC, 0.015A priority relay actuation and an OFF position. Stainless steel faceplate with embossed positions and a black knob with white indicator mark.



<b>APPLICATION</b>	<b>Intended Use:</b>	Indoor environment
	<b>Primary Use:</b>	Attenuates audio level output to any number of loudspeakers up to 20W load For use with 25V or 70V distributed audio systems. When internal 24VDC relay is activated, attenuator function is bypassed
	<b>Installation:</b>	Single-gang electrical box, 2 1/8" deep
<b>AUDIO PERFORMANCE</b>	<b>Power Rating:</b>	20W Continuous
	<b>Attenuation (Ref:25V, 70.7V line):</b>	Position 10 : Full Signal Position 9-3 : -3dB Each Position 2-1 : -6dB Each Position 0 : No Signal
	<b>Relay Actuation:</b>	24 VDC, 0.015A
	<b>Insertion Loss:</b>	< 0.5dB
	<b>Audio Connection:</b>	10", Color-coded, Pre-tinned Leads
<b>COMPONENT</b>	<b>Dimension:</b>	4 9/16" (H) x 2 13/16" (W) x 2 1/4" (D)
	<b>Weight:</b>	1 lbs.
	<b>Faceplate:</b>	Brushed, stainless steel with embossed positions
	<b>Other:</b>	Black knob with white indicator mark
	<b>RECOMMENDED QUAM COMPONENTS</b>	<b>Enclosures:</b>

