



## WattBox Power Conditioner with Coax and Ethernet Protection - 4 Outlets

Whether it's a structured wiring can, flat panel TV or cabinet – the WB-200-CE power conditioner provides premium surge protection and noise filtration to 4 outlets, as well as coax and Telephone/ Ethernet protection. And don't let its size fool you. Its outside is just as rugged as the protection it offers, with an 18-gauge steel chassis and built-in wings for mounting.

#### INSTALLABILITY IS KEY

Our product team designed this WattBox 200-series power conditioner with a slim form factor and integrated mounting ears. The mounting holes line up with a range of install soltuions for a quick and easy install.

#### FIREPROOF MOVS

MOVs, or Metal Oxide Varistors, are surge protection components that dissipate excess energy in the form of heat. WattBox power conditioners feature ceramic-encased MOVs to protect not only your system but your home as well.

#### **POWER ADAPTERS WELCOME**

Bulky power supplies, or wall warts, can be a real pain to deal with during the install. We've oriented the outlets to make them easier to plug in when installing against the wall, cabinet, or in a structured wiring can.



# WattBox Power Conditioner with Coax and Ethernet Protection – 4 Outlets

### WB-200-CE-4

Breaker Switch Rating	15A
Coaxial Protection	1 ln – 1 Out
Current Rating	12A
Connected Equipment Warranty	25,000
Fireproof MOV	Yes
Isolated Filter Banks	1
Energy Dissipation (Joules)	2160
Optional Faceplate Display	No
Outlets	4
Outlets Switched	All
Safe Voltage	No
Sequencing	No
Telephone & Network Protection	1 ln – 1 Out
Voltage Protection Rating	500V
12V Trigger	No
Certifications	UL 60950-1, UL 1449, UL 498, UL 497A/B, UL 1283
Dimensions (W x H x D)	5.21" x 1.73" x 3.89"
Power Cord Length	4 Ft.
Line Voltage	120V AC, 60Hz
Rack Mountable	No