

26886, 22429 - USB TO SERIAL ADAPTER

System Requirements:

- Windows® XP, Vista, 7, 8, 8.1
- One available USB port

Package Contents:

26886

- USB to DB9 serial adapter
- Driver CD
- Quick start guide

22429

- USB to DB25 serial adapter
- Driver CD
- Quick start guide

Device Installation:

Step 1: Insert the CD into the computer's CD drive, click on the 26886 and 22429 - USB to Serial Adapter button, and then click on the Install Driver button.

Note: If AutoPlay is not enabled on the computer, then locate and double-click the Setup.exe file through Windows Explorer (Computer or My Computer) on the CD drive.

Step 2: Follow the prompts in the Install Shield to complete the installation of the driver.

Step 3: Reboot the computer to complete the installation

Step 4: Connect the serial device to the USB to serial adapter using a separate serial cable with the proper pinout for the serial device.

Step 5: Connect the USB to Serial adapter to an available USB port on the computer after the computer has fully rebooted.

Installation Verification

Step 1: Open the Control Panel and then open the Device Manager.

Step 2: Expand the category labeled Ports (COM & LPT).

Step 3: The adapter will appear under this category as Prolific USB to Serial (COM X), where "X" represents the COM port number that has been assigned to the adapter.

Changing the COM port number:

Note: Windows® will automatically assign a COM port number to the USB to Serial adapter when the adapter is connected to the computer. Use the instructions below to change the COM port number.

Step 1: Open the Control Panel and then open the Device Manager.

Step 2: Expand the category labeled Ports (COM & LPT).

Step 3: Right click on the listing of Prolific USB to Serial (COM X), where "X" represents the COM port number that has been assigned to the adapter, and select Properties.

Step 4: Click on the Port Settings tab and then click on the Advanced button.

Step 5: Use the dropdown box labeled COM Port Number to select an available COM port number

Technical Specifications:

	26886	22429
USB Specification	1.1 & 2.0	
Connectors	USB A Male x 1 DB9 Male x 1	USB A Male x 1 DB25 Male x 1
Cable Length	1.5ft	6 ft
Cable Weight	1.2 lbs	
Color	Blue	