


MLRK1-MRK

MARKS M9000 SERIES

- **PUSH TO SET TECHNOLOGY**
- **EASY INSTALLATION - FAST, QUIET, SMOOTH**
- **TRUE ELECTRONIC DOGGING - FULL PUSH PAD RETRACTION**
- **UL LISTED**
- **3 YEAR WARRANTY**



The **MLRK1-MRK** is a robust, straightforward field-installable motorized latch retraction kit for Marks M9900 & Design Hardware 1000 series exit devices. It utilizes a CAT-designed custom assembly to maximize the pulling force. The only hole you'll need to drill is the raceway! It uses our new 1-touch PTS "Push to Set" technology, making post-installation adjustments a breeze. An optional built-in REX switch is available on all units!

SPECIFICATIONS

Voltage:

- Voltage range – 24VDC +/- 10%
- System protection - unit shutdown when voltage exceeds 28VDC
- Standard - Average Current Peak: 900mA, Average Current Hold: 200mA
- PTS adjustment - approx. 1/4"

Wire Run:

- 300' with 18ga wire

Cutdown:

- 36" - 1-1/4"
- 48" - 1-1/4"

Accessories

- Request-to-Exit - Field Installable REX kit
- Latchbolt Monitor Switch
- Door Position Switch

Product Details:

- Weight: 2 Lbs
- Box: 14.25" L x 2.5" H x 6" W

FEATURES

- Next Generation MM5 Smart Module: On board diagnostics with audible feedback for adjustment and power issues.
- "PTS": 2 second electronic adjustment for easy post installation adjustment. Simplified further with a push button to engage programming & shorter program sequence.
- Standard Torque Mode: Now capable of pulling all types of devices, even the difficult tall Vertical Rods doors!
- Electric dogging rated for continuous duty - Auto reengage if push pad is pulled from dogged position
- Up to 300' wire run with 2-18ga wire - Long wire runs provides installer with convenience of placing the Command locking hardware power supply in a centralized location; i.e. the same closet as the access control panel.
- Request-to-exit kit available
- 3-year "no hassle" warranty

HOW TO ORDER

PART #	EASY ORDER #	DESCRIPTION
MLRK1-MRK	72626	Kit for Marks M9900 & Design Hardware 1000 series. EU 24V
MLRK1-MRK REX	72627	Kit for Marks M9900 & Design Hardware 1000 series. EU 24V w/ REX
MRKREXKIT-M-ED	72469	REX Kit add on for the MLRK1-MRK. EU 24V

MLRK1-MRK MATRIX

The MLRK1-MRK will work in new installations and as a replacement for installations with existing electrifications, matrix lists available options.

Marks/Design Hardware Kit	Mechanical Device	CAT Modified Solenoid	CAT Modified Motor	Marks Motor	SDC Motor (LR100-MDK)	ACSI Motor (1550K-MDH)
MRK		-			-	

NEED A LOCKING HARDWARE POWER SUPPLY?

RECOMMENDED LOCKING HARDWARE POWER SUPPLIES:

- PS204/PS204B
- PS220/220B
- PS480B
- PS210
- PS440B

