

1080p Penta-brid HDCVI DVR

32-Channel 1.5U Digital Video Recorder with Analytics+





WizSense Series devices combine Dahua's powerful Analytics+ with an intuitive and easy to use interface. WizSense devices offer Smart Motion Detection and Perimeter Protection functions that focus on human and vehicular images and ignore irrelevant images to capture important video while reducing false alarms. WizSense Series devices provide powerful general surveillance for small to medium size businesses at a sensible price.

System Overview

The X54B5L Series HDCVI DVR offers 5M-N/1080p recording on each HDCVI channel and a host of advanced features and functions. The DVR takes advantage of HDCVI technology for easy integration into existing video surveillance systems while leveraging existing networks, cabling, and cameras. Penta-brid access technology seamlessly records video from HDCVI, AHD, TVI, CVBS, and IP sources simultaneously. This recorder is the ideal solution for actively monitoring public venues, retail stores, transportation hubs and access ways, personal property and homes, and educational institutions.

Functions

Perimeter Protection

Dahua Analytics+ includes Tripwire and Intrusion functions that offer custom tripwires based on object type for automation in limited access areas. Perimeter Protection requires less pixels to detect an object to deliver improved accuracy and decreased false alarms due to lights, weather, trees, or animals.

Smart Motion Detection

The Smart Motion Detection, a component of Dahua's Analytics+ technology, improves alarm accuracy and decreases the number of false alarms. The advanced SMD algorithm analyzes a scene for human or vehicle motion, while filtering out other motion due to trees, leaves, animals, weather, and triggers an alarm when detected.

- 1080p at 30 fps Recording Resolution on All HDCVI Channels
- Available with a 4 TB, 6 TB, 8 TB, or 10 TB Pre-installed Hard Drive
- Dual-stream Video Recording
- Al Coding Technology for High-quality Human/Vehicle Video
- Auto-detection and Auto-configuration of Video Inputs
- 32 IP Camera Channels, each channel up to 8 MP
- Maximum 128 Mbps Incoming Bandwidth
- Spot Output
- Perimeter Protection and Smart Motion Detection (SMD)
- Long-distance Video Transmission
- Five-year Warranty*













Camera Connections

Record and monitor video from analog/HDCVI camera inputs and IP camera inputs simultaneously. The X58A series supports a maximum of 32 channels, with up to 32 channels of HDCVI/AHD/TVI/CVBS/IP inputs. The flexibility of the HDCVI DVR allows all 32 channels to record input from IP cameras, or from a combination of input from analog and IP sources (not to exceed the maximum number of analog cameras allowed per recorder)

AI Coding

The AI Coding function puts recording emphasis on human or vehicular objects in the video scene. This technology, based on constant bit rate (CBR), dynamically allocates increased bit rate to the target object while reducing the bit rate allocated to background objects. AI Coding reduces bit rate and storage requirements by up to 50% when compared to the H.265 video compression standard.

Smart H.265+

Smart H.265+ is the optimized implementation of the H.265 codec that uses a scene-adaptive encoding strategy, dynamic GOP, dynamic ROI, flexible multi-frame reference structure and intelligent noise reduction to deliver high-quality video without straining the network. Smart H.265+ technology reduces bit rate and storage requirements by up to 90% when compared to the H.264 video compression standard.

HDCVI/AHD/TVI/CVBS Auto-detect

The HDCVI DVR automatically recognizes the incoming signals of each attached camera without any setup, making installation easy and operation convenient.

Long Distance Transmission

HDCVI technology guarantees real-time transmission over long distances without loss of video quality. HDCVI devices provide the same resolution as most IP network camera systems using existing RG-59, RG-6, or CAT 6 UTP cabling.

Pro Series | X54B5L Series

Playback

Technical Specification			
System			
Main Processor	Embedded Processor		
Operating System	Embedded LINUX		
Analytics+ Perimeter Protection ¹			
Performance	Human and Vehicle object classification Decreased false alarms from leaves, lights, animals Configure function on two (2) analog channels In Tripwire/Intrusion rules per channel		
Live View	Configure Rule and Object Inspection area Display object classification, event types, trigger time, image snapshot, and object types Export event playback 10 seconds prior to or after event		
Playback	Search by channel, time, event type, and target type Search event playback 10 seconds prior to or after event Snapshot capacity: 500,000		
Analytics+ Smart Motion Detection ¹			
Performance	Detect motion based on object classification (human or vehicle) Decreased false alarms from leaves, lights, animals Configure functions on 16 analog channels		
Preview	Configure and inspect detection area		
	• Search by channel, time, event type, and target type		

event

• Search event playback 10 seconds prior to or after

Interface				
Analog Camera Input		32 Channels, BNC		
HDCVI		5 MP, 4 MP, 1080p, 720p		
AHD		5 MP, 4 MP, 1080p, 720p		
TVI		5 MP, 4 MP, 1080p, 720p		
CVBS		NTSC		
IP Camera Input		32 Channels, each channel up to 8 MP (The recording rate is dependent on the maximum resolution and frame rate of the connected IP camera.)		
Audio		Input: Four (4) Channels, BNC Output: One (1) Channel, BNC		
Two-way Talk		One (1) Microphone Input (BNC) and One (1) Microphone Output (BNC)		
Recording				
Compression		Al Coding, Smart H.265+, H.265, Smart H.264+, H.264		
Recording Resolution ²		5 M-N, 4 M-N, 1080p, 1080N, 720p, 960H, D1, CIF (The recording rate is dependent on the maximum resolution and frame rate of the connected IP camera.)		
Record Rate	Main Stream	5 M-N at 20 fps 4 M-N, 1080p, 1080N, 720p, 960H, D1, or CIF at 30 fps		
	Sub Stream	D1 or CIF at 15 fps		
Max. Incoming E	Bandwidth	128 Mbps		
Bit Rate		32 Kbps to 6144 Kbps per Channel		
Record Mode		Manual, Schedule (Regular, Continuous), MD (Video Detection: Motion Detection, Video Loss, Tampering), Alarm, Stop		
Record Interval		1 to 60 minutes (default: 60 minutes), Pre-record: 1 s to 30 s, Post-record: 10 s to 300 s		
Audio Compression		G.711a, G.711Mu, PCM		
Audio Sample Rate		8 KHz, 16 bits per Channel		
Audio Bit Rate		64 Kbps per Channel		

The recorder is capable of two (2) simultaneous Perimeter Protection channels, 16 SMD channels, or one (1) Perimeter Protectio channel and eight (8) SMD channels. Perimeter Protection and SMD cannot be used on the same channel.

The M-N resolution refers to technology that allows a 1080p HDCVI DVR to accept a video signal from a 5 MP or a 4 MP camera by sampling every other pixel on a horizontal line from the camera. The resulting recording resolutions are: 5 M-N: 1296 x 1944; 4 M-N: 1280 x 1440.

RS232

Display			Electrical		
Interface		Two (2) HDMI (3840 x 2160) Ports One (1) VGA (1920 x 1080) Port One (1) TV Port	Power Supply	100 VAC to 240 VAC, 50/60Hz	
			Power Consumption	< 22 W, without HDD	
Spot Output		HDMI 2	Construction		
HDMI 1 Native Output	3840 x 2160, 2560 x 1440, 1920 x 1080, 1280 x 1024, 1280 x 720	Dimensions	1.5U, 440.0 mm x 420.20 mm x 76.0 mm (17.32 in. x 16.54 in. x 2.99 in.)		
Resolution	HDMI 2/ VGA	1920 x 1080, 1280 x 1024, 1280 x 720	Net Weight	4.80 kg (10.70 lb)	
	VGA	16 Channels of 5M-N at 10 fps 16 Channels of 4M-N at 15 fps 16 Channels of 1080N/720p at 30 fps Eight (8) Channels of 5M-N at 20 fps	Gross Weight	7.10 kg (15.60 lb)	
			Installation	Desktop or Rack-mount	
Maximum Playb	ack		Video Transmission	Distance	
Decoding		Eight (8) Channels of 4M-N at 30 fps Four (4) Channels of 5M-N at 30 fps One (1) Channel of 8 MP at 30fps	RG-59/U Coax	720p: 800 m (2624.67 ft) 1080p: 500 m (1640.42 ft) 4K/4MP: 500 m (1640.42 ft)	
Multi-screen Dis	splay	1/4/8/9/16/25/36	RG-6/U Coax	720p: 1200 m (3937.01 ft) 1080p: 800 m (2624.67 ft)	
On-screen Displa	ay	Camera Title, Time, Video Loss, Camera Lock, Motion Detection, Recording		4K/4MP: 700 m (2296.59 ft) 720p: 450 m (1476.38 ft)	
Network			CAT 6 UTP (balun required)	1080p: 300 m (984.25 ft) 4K/4MP: 300 m (984.25 ft)	
Interface		One (1) RJ-45 (1000 Mbps) Port	Environmental		
Network Function	n	HTTP, TCP/IP, IPv4/IPv6, UPnP, RTSP, UDP, SMTP, NTP, DHCP, DNS, IP Filter, PPP0E,DDNS, FTP, Alarm Server, P2P, IP Search	Operating Conditions	-10° C to +55° C (+14° F to +131° F), 0% to 90% RH	
NA-visson Harri		(Supports Dahua IP cameras, DVRs, NVS)	Storage Conditions	–20° C to +70° C (–4°F to +158° F), 0% to 90% RH	
Maximum User A	Access	128 Users	Third-party Suppor	t	
Mobile Operating System IOS, Android		IOS, Android ONVIF 16.12, CGI Conformant	Third-party Support	Dahua, Arecont Vision, AXIS, Bosch, Brickcom, Canon, C Plus, Dynacolor, Honeywell, Panasonic, Pelco, Samsung	
Interoperability ONVIF 16.12, CGI Conformant Video Detection and Alarm				Sanyo, Sony, Videotec, Vivotek, and others	
video Detec		Recording, PTZ, Tour, Video Push, Email, FTP, Snapshot, Buzzer	Certifications		
Trigger Events an		and Screen Tips Motion Detection, MD Zones: 396 (22 × 18),	Safety	EN 60950-1 IEC 60950-1	
Video Detection		Video Loss, Tampering, and Diagnosis		FCC CFR 47 Part 15 Subpart B	
Alarm Input		16 Channels	Electromagnetic	EN 61000-3-2	
Relay Output		Six (6) Channels	Electromagnetic Compatibility (EMC)	EN 61000-3-3 EN 55032	
Playback and	d Backup			EN 50130 EN 55024	
Playback		1/4/9/16			
Search Mode		Time/Date, Alarm, MD and Exact Search (accurate to 1 second)			
Playback Function	n	Play, Pause, Stop, Rewind, Fast Play, Slow Play, Next File, Previous File, Next Camera, Previous Camera, Full Screen, Repeat, Shuffle, Backup Selection, and Digital Zoom			
Backup Mode		USB Device/Network			
Storage					
Internal HDD F		Four (4) SATA Ports, up to 10 TB capacity for each disk			
eSATA One (1) Port					
Auxiliary Inte	erface				
USB		One (1) USB 2.0 Port and Two (2) USB 3.0 Ports			
RS485		One (1) Port for PTZ Control			

One (1) Port for PC Communication and Keyboard

Ordering Information							
Туре	Part Number	Description					
1080p HDCVI DVR with Analytics+	X54B5L	32-Channel Penta-brid 1080p 1.5U Digital Video Recorder, No pre-installed HDD					
	X54B5L4	32-Channel Penta-brid 1080p 1.5U, 4 TB Digital Video Recorder					
	X54B5L6	32-Channel Penta-brid 1080p 1.5U, 6 TB Digital Video Recorder					
	X54B5L8	32-Channel Penta-brid 1080p 1.5U, 8 TB Digital Video Recorder					
	X54B5L10	32-Channel Penta-brid 1080p 1.5U, 10 TB Digital Video Recorder					
Rear Panel							
1234 5	7	11 12 14 15					
6 8 9 10 13 16							

1	Microphone Output, BNC	9	RS232 (Ethernet Port)
2	Microphone Input, BNC	10	USB Port
3	Video Out, BNC	11	VGA Output
4	Audio Output, BNC	12	eSATA Port
5	Audio Input, x4 BNC	13	HDMI Output, x2
6	Video Input, x32 BNC	14	Power Switch
7	Alarm Input, x16 Alarm Output, x6	15	Power Input
8	RJ-45 Ethernet Port (1000 Mbps)	16	Ground





