Arlington[®]

ONE-BOX™ Vapor Boxes for Devices



F101F



FN102F



F103F



FN104FD



Versatile, non-conductive outlet box for new construction. Mounts directly to a wood. **FEATURES AND BENEFITS**

- Fast and easy to install
- Mounts directly to a wood or steel stud for a super secure installation
- Flange forms a protective barrier against air infiltration
- *2-hour fire rating

CATALOG NUMBER	UPC/DCI/NAED MFG #018997	DESCRIPTION/ CU. IN.	UNIT PKG	STD PKG	DIM A	DIM B	DIM C	DIM D
F101F	12520	Single-gang Screw-on/22.0	25	25	5.990	4.500	3.510	.500
F102F	06900	2-Gang Screw-on/42.0	10	10	5.990	6.313	3.510	.500
F103F	06901	3-Gang Screw-on/59.0	10	10	5.990	8.125	3.510	.500
F104F	06902	4-Gang Screw-on/81.0	10	10	5.990	9.937	3.510	.500
FN101F	15130	Single-gang Nail-on/23.0	20	20	5.990	4.500	3.510	.500
FN102F	15132	2-Gang Nail-on/43.5	10	10	5.990	6.313	3.510	.500
FN103F	15134	3-Gang Nail-on/63.5	10	10	5.990	8.125	3.510	.500
FN104F	15136	4-Gang Nail-on/85.3	10	10	5.990	9.937	3.510	.500
FN101FD*	15131	Single-gang double drywall nail-on/28.0	20	20	5.990	4.500	4.344	1.312
FN102FD*	15133	2-Gang double drywall nail-on/53.0	10	10	5.990	6.312	4.344	1.312
FN103FD*	15135	3-Gang double drywall nail-on/77.8	10	10	5.990	8.124	4.344	1.312
FN104FD*	15137	4-Gang double drywall nail-on/103.5	10	10	5.990	9.936	4.344	1.312

*For use with double drywall installation and has a two-hour fire rating. Add suffix "GC" to Catalog # when ordering in Canada to include grounding clip, for example F101FGC.

Refer to R-1 and R-2 for additional Vapor Boxes.

PATENTED.



Multi-gang boxes work with the F102D divider.

FEATURES AND BENEFITS

Add divider for power/low-voltage applications.

See page Q-1 for ordering details.



NEW! Installed NM cable connectors with gasket material attached.

Saves time—Pull wire through; knockouts are sealed

